

SM2161M

Two-wire current-type protection type 200,000-range illuminance sensor

User Manual

File Version: V21.3.24




SM2161M using the standard DC4-20mA current output signal,easy access to PLC , DCS and other instruments or systems for monitoring Illuminance state quantities.The internal use of high -precision sensing core and related devices to ensure high reliability and excellent long-term stability,can be customized RS232,RS485,CAN,4-20mA,DC0~5V\10V,ZIGBEE,Lora,WIFI,GPRS and other output methods.


Technical Parameters

Technical parameter	Parameter value
Brand	SONBEST
Illuminance measuring range	0~20 0000Lux
Illuminance allow deviation	± 7%
Repeatability test	± 5%
Illuminance detection chip	Import digital
Wavelength range	380nm~730nm
Communication Interface	DC4~20mA
Power	DC12~24V 1A
Running temperature	-40~80°C
Working humidity	5%RH~90%RH

Product Size



How to wiring?



RS485 Wire

	RD	PWR+
	GN	PWR-
	YE	RS485 A+
	BU	RS485 B-

Electric current two-wire

	RD	Ammeter-
	BK	PWR-

Electric current three-wire

	RD	PWR+
	BK	PWR-
	BU	I OUT


Voltage type wire

	RD	PWR+
	BK	PWR-
	BU	V OUT


※Note: When wiring, first connect the positive and negative poles of the power supply, and then connect the signal line

Application solution


■ RS485 Wiring




■ Current two-wire system wiring



■ Current three-wire system wiring



■ Voltage wiring



How to use?



Greenhouse

Cooperate with sensors to effectively manage, create a good lighting environment for crops, and promote better photosynthesis

Flower farming

Flower farming needs light management, according to the plant's light needs to cooperate with the sensor to control the light intensity





Disclaimer

This document provides all information about the product, does not grant any license to intellectual property, does not express or imply, and prohibits any other means of granting any intellectual property rights, such as the statement of sales terms and conditions of this product, other issues. No liability is assumed. Furthermore, our company makes no warranties, express or implied, regarding the sale and use of this product, including the suitability for the specific use of the product, the marketability or the infringement liability for any patent, copyright or other intellectual property rights, etc. Product specifications and product descriptions may be modified at any time without notice.

Contact Us

Company: Shanghai Sonbest Industrial Co., Ltd

Address: Building 8, No. 215 North east road, Baoshan District, Shanghai, China

Web: <http://www.sonbest.com>

Web: <http://www.sonbus.com>

SKYPE: soobuu

Email: sale@sonbest.com

Tel: 86-021-51083595 / 66862055 / 66862075 / 66861077