# SM3560M2

# 4-20mA current type 0-10000 lux range illuminance sensor

### **User Manual**

File Version: V21.12.15



SM3560M2 using the standard DC4-20mA current output signal,easy access to PLC, DCS and other instruments or systems for monitoring illuminance state quantities. The internal use of high-precision sensing core and related devices to ensure high reliability and excellent long-term stability,can be customized RS232,RS485,CAN,4-20mA,DC0~5V\10V,ZIGBEE,Lora,WIFI,GPRS and other output methods.

### **Technical Parameters**

Technical parameter	Parameter value

SONBEST

http://www.sonbus.com/


Brand	SONBEST	
Illuminance measuring range	0~20000Lux	
Illuminance allow deviation	±7%	
Repeatability test	$\pm$ 5%	
Illuminance detection chip	Import digital	
Wavelength range	380nm~730nm	
Communication Interface	DC4~20mA	
Power	DC12~24V 1A	
Running temperature	-40~80°C	
Working humidity	5%RH~90%RH	

#### Wiring instructions

Any incorrect wiring can cause irreversible damage to the product. Please carefully wire the cable as follows in the case of power failure, and then connect the cable to confirm the correctness and then use it again.

ID	Core color	Identification	Note
1	Red	V+	Power V+
2	Blue	+	sensor output
3	BLACK	V-	Power negative electrode

In the case of broken wires, wire the wires as shown in the figure. If the product itself has no leads, the core color is for reference.



### Disclaimer

This document provides all information about the product, does not grant any license to intellectual property, does not express or imply, and prohibits any other means of granting any intellectual property rights, such as the statement of sales terms and conditions of this product, other issues. No liability is assumed. Furthermore, our company makes no warranties, express or implied, regarding the sale and use of this product, including the suitability for the specific use of the product, the marketability or the infringement liability for any patent, copyright or other intellectual property rights, etc. Product specifications and product descriptions may be modified at any time without notice.

### **Contact Us**

Company: Shanghai Sonbest Industrial Co., Ltd Address:Building 8,No.215 North east road,Baoshan District,Shanghai,China Web: http://www.sonbest.com Web: http://www.sonbus.com SKYPE: soobuu Email: sale@sonbest.com Tel: 86-021-51083595 / 66862055 / 66862075 / 66861077